

Air-Cooled Standby Generator



Available in 14kW, 18kW, 22kW, 24kW, 26kW, and 28kW

The Generac Standby Generator is the most advanced air-cooled standby generator providing unparalleled peace of mind. It provides the automatic backup power you need to help protect your home and family during a power outage. Connected to your existing LP or natural gas fuel supply, it kicks in within seconds of sensing power loss—automatically—and runs for as long as necessary until utility power returns.



Cellular Connectivity

Built-in Cellular Connectivity allows you to monitor performance and control your generator with Mobile Link whether you're home or away.



Cost of Ownership

Lowest total cost of ownership.*

**Based on MSRP + average maintenance cost of equivalent solutions.*




Seamless Energy Integration

Compatible with ecobee by Generac thermostats and Generac PWRcell battery systems to seamlessly monitor and control your home's energy.



Unmatched Power

28kW is the most powerful air-cooled standby generator in the market, setting a new standard for whole-home backup power.



Improved Performance

Electronic Fuel and Emission Control to adjust to the environment which improves cold starting and performance when operated in cold climates.

Get an estimate today!



24/7/365 Customer Support Team

Standing by all day, every day from our headquarters in Wisconsin to answer any questions you might have.



Built in the USA*

Generac generators, engines and automatic transfer switches are engineered and built in the USA.*

**Assembled in the USA using domestic and foreign parts*



5-Year Limited Warranty

Included with all air-cooled standby generators.

Air-Cooled Standby Generators



SPECIFICATIONS (LP/NG)	14kW	18kW	22kW	24kW	26kW	28kW
Generator Only Model	7258	7259	7260	7261	7327	7282
Generator / 200 Amp Auto Transfer Switch	7323	7324	7325	7326	7328	7329
Rated kW LPG/NG*	14/14*	18/17*	22/21 *	24/22.5 *	26/24 *	28/25 *
Voltage (Single Phase)	240					
Amps @ 240V LPG*	58	75	92	100	108	116
Amps @ 240V NG*	58	71	88	94	100	104
Operating RPM	3600					
Engine	Generac G-Force 800 Series			Generac G-Force 1000 Series		
Engine Displacement	817cc			997cc		
Electronic Fuel and Ignition Control (EFIC)	Yes					
Hydraulic Lifters	Yes					
Fuel Consumption @ ½ Load – NG cu. ft/hr	189	164	221	197	182	182
Fuel Consumption @ Full Load – NG cu. ft/hr	243	235	311	291	316	297
Fuel Consumption @ ½ Load – LPG cu. ft/hr (gal/hr)	63 (1.76)	w (1.65)	89 (2.45)	89 (2.45)	74 (2.05)	81 (2.23)
Fuel Consumption @ Full Load – LPG cu. ft/hr (gal/hr)	106 (2.92)	105 (2.87)	135 (3.71)	135 (3.71)	144 (3.95)	144 (3.97)
Quiet-Test Mode	Yes					
Smart Exercise	Yes					
Exercise with Transfer of Power	Yes					
db(A) at Low Speed Exercise (Quiet-Test Mode)	55					
db(A) at Normal Operating Load	65			67		
Enclosure	Aluminum					
Enclosure Color	Metro Gray					
Warranty	5 – Year Limited					
Dimensions (L x W x H) in/cm	46.4 x 26.3 x 30.7 / 117.9 x 66.8 x 77.9					
Weight (lb)	391	426	451	461	524	524
Mobile Link Cellular Connectivity as Standard	Yes					

*Maximum kilovolt amps and current are subject to and limited by such factors as fuel BTU/megajoule content, ambient temperature, humidity, barometric pressure, altitude, engine power and condition, etc. Maximum power decreases approximately 3.5% for each 1,000 ft (304.8 m) above sea level; and also will decrease approximately 1% for each 10 °F (6 °C) above 60 °F (16 °C).

NATIONWIDE INSTALLER SERVICE NETWORK

Generac's commitment to service includes scheduled maintenance programs, warranty assistance and emergency service to help ensure that Generac customers are never left powerless. The largest nationwide network has factory-trained technicians on staff and maintains large inventories of Generac parts, components and accessories. Find an installer near you at Generac.com.

GENERAC®

Generac Power Systems, Inc.
S45 W29290 Hwy. 59, Waukesha, WI 53189

www.Generac.com | 888-GENERAC (436-3722)

201911325 REV 10/25

©2025 Generac Power Systems. All rights reserved.
Specifications are subject to change without notice.

qcdata_SYS